

Single phase , 200~240V model					
Model	FID-L2-002-21	FID-L2-004-21	FID-L2-007-21	FID-L2-015-21	FID-L2-022-21
Horsepower(HP)	0.25	0.5	1	2	3
Max Applicable Motor Output (KW)	0.2	0.4	0.75	1.5	2.2
Rated Output Current (A)	1.8	2.6	4.3	7.5	10.5
Rated Capacity (KVA)	0.68	1.00	1.65	2.90	4.00
Max. Input Voltage	Single phase , 200~240V(+10%/-15%), 50/60Hz				
Max. Output Voltage	Three phase 0~240V				
Input Current (A)	4.9	7.2	11	15.5	21
Allowable Momentary Power Loss Time (Second)	1.0	1.0	1.0	2.0	2.0
Ingress Protection (IP) Level	IP20				

200V Class : Single phase				
Model	FID-E2-004-2A	FID-E2-007-2A	FID-E2-015-2A	FID-E2-022-2A
Horsepower/Motor Capacity (HP)/(KW)	0.5 (0.4)	1 (0.75)	2 (1.5)	3 (2.2)
Rated Output Current (A)	2.6	4.3	7.5	10.5
Rated Capacity (KVA)	1	1.65	2.9	4
Input Voltage Range (V)	Single phase , 200~240V(+10%-15%), 50/60Hz			
Output Voltage Range (V)	Three phase 0~240V			
Input Current (A)	7.2	11	15.5	21
Inverter N.W. (KG)	0.67	0.67	1	1.05
Inverter with Filter (KG)	0.73	0.73	1.25	1.3
Allowable Momentary Power Loss Time (Second)	1	1	2	2
Ingress Protection (IP) Level	IP20			

400V Class : Three phase									
Model	FID-E2-007-43	FID-E2-015-43	FID-E2-022-43	FID-E2-037-43	FID-E2-055-43	FID-E2-075-43	FID-E2-110-43	FID-E2-150-43	FID-E2-185-43
Horsepower/Motor Capacity (HP)/(KW)	1 (0.75)	2 (1.5)	3 (2.2)	5 (3.7)	7.5 (5.5)	10 (7.5)	15 (11)	20 (15)	25 (18.5)
Rated Output Current (A)	2.3	3.8	5.2	8.8	13	17.5	24	32	40
Rated Capacity (KVA)	1.7	2.9	4	6.7	9.9	13.3	19.1	27.4	34
Input Voltage Range (V)	Three phase , 380~480V(+10%-15%), 50/60Hz								
Output Voltage Range (V)	Three phase 0~480V								
Input Current (A)	4.2	5.6	7.3	11.6	17	23	31	38	48
Inverter N.W. (KG)	1.2	1.2	1.8	1.8	6.25	6.25	6.25	15	15
Inverter with Filter (KG)	1.3	1.3	2.2	2.2	6.75	6.75	6.75	17.0	17.0
Allowable Momentary Power Loss Time (Second)	2	2	2	2	1	1	1	2	2
Ingress Protection (IP) Level	IP20								